



## Data Sheet Sensor Beacon Go Mini

### Features

- Sensors: acceleration, tilt, temperature, magnetic field
- Provision of the sensor values via blukii Sensor Beacon Protocol
- Three sensor packages can be selected / deselected via the blukii Configurator App, which transmit the sensor data one after the other according to the set advertising interval
  - Environmental (temperature)
  - Magnetometer (magnetic field)
  - Acceleration (acceleration and tilt)
- Bluetooth Low Energy® 4.2
- Management and setting of all parameters via blukii Manager and blukii Configurator App
- Individual pre-configuration possible (MOQ: 20 pieces)



### Advertising

Beacon protocols	iBeacon, blukii Sensor Beacon Protocol
Advertising interval	0,1s to 10s (adjustable) Default: 1s

### Radio

Standard	Bluetooth 4.2 (Bluetooth Low Energy)
Controller	Texas Instruments CC2640
Range	Up to 100m
Frequency range	2.402 to 2.480GHz
TX-Power (adjustable)	High(5dBm) / Medium(0dBm) / Low(-9dBm) / Lowest(-20dBm)
Antenna	Customized OnBoard SMD-Antenna

### Sensors

Acceleration / Tilt	0-2g (3-Axis)
Temperature	-40°C to +85°C
Magnetic field	+/-1,6mT

### Battery

Type	Lithium-manganese-dioxide
Model	Sony CR2032 3V/220mAh
Capacity	220mAh
Replaceable	Yes
Lifetime at Advertising interval 0,3s (TX-Power: +5dBm)	0,14 years
Lifetime at Advertising interval 1s (TX-Power: +5dBm)	0,5 years

### Mechanical specifications

Enclosure material	Copolyester
Colour	white
Protection Class	IP62
Flammability rating	UL94HB
Dimensions	22x7mm
Weight	6g



### Environmental requirements

Operating temperature	-20°C to +60°C (Lifetime drops sharply under 0°C )
-----------------------	----------------------------------------------------

### Certifications

CE (2014/53/EU, 2011/65/EU)
-----------------------------